

1. MOV R7,#9H  
AG1: MOV P2#00  
AG: LCALL DELAY  
INC P2  
MOV A,P2  
CJNE A,#0AH,AG  
SJMP AG1  
RET

2. JNB P0.0,ZE  
MOV P2,#01  
RET  
ZE: MOV P2,#00  
RET

3. MOV A,P0  
MOV 20H,#00  
R1: RL  
JNC R2  
INC 20H  
R2: DJNZ R7,R1  
MOV P2,20H  
RET

4. MOV A,P0  
RR A  
JNC XX  
MOV P2,#01  
RET  
XX: MOV P2,#00  
RET

5. MOV R6,#9  
MOV P2,#00  
LO: MOV R7,P0  
DJNZ R7,\$  
INC P2  
DJNZ R6,LO  
RET

6. MOV A,P0  
CLR C  
SUBB A,#50H  
JNC BIG  
MOV P2,#00111100B  
RET  
BIG: MOV P2,#00111111B  
RET

7. MOV A,P0  
 ANL A,#00000011B  
 CJNE A,#03,XX  
 MOV P2,#2  
 SJMP SOF  
 XX: MOV P2,#00  
 SOF: RET

### פתרונות תרגילים-איור 2

1. MOV R7,#9  
MOV P2,#00  
ST: LCALL DEL  
INC P2  
DJNZ R7,ST  
RET
2. MOV A,#01  
MOV R7,#7  
DD: MOV P2,A  
LCALL DEL  
RL A  
ADD A,#1  
DJNZ R7,DD  
RET
3. MOV A,P0  
CPL A  
MOV P2,A  
RET
4. AG: MOV R7,P0  
MOV P2,#00  
DJNZ R7,\$  
MOV R7,P0  
MOV P2,#0FFH  
DJNZ R7,\$  
SJMP AG  
RET
5. MOV A,P0  
MOV R0,#00  
MOV R7,#8  
WW: RL A  
JC DA  
INC R0  
DA: DJNZ R7,WW  
MOV A,R0  
SWAP A  
MOV P2,A  
RET

6.

MOV	A,P0
ANL	A,#0FH
MOV	R7,A
MOV	R6,#80
MOV	A,#01
AGA:	MOV P2,A
	MOV 20H,R7
	DJNZ 20H,\$
	RL A
	DJNZ R6,AGA
	RET

7.

SS:	MOV A,P0
	CJNE A,#00,SS1
	SJMP SS
SS1:	JNB P0.0,SS2
	SETB P2.0
SS2:	JNB P0.1,SS3
	SETB P2.1
SS3:	JNB P0.2,SS4
	SETB P2.2
SS4:	JNB P0.3,SS5
	SETB P2.3
SS5:	JNB P0.4,SS6
	SETB P2.4
SS6:	JNB P0.5,SS2
	SETB P2.5
SS7:	JNB P0.6,SS8
	SETB P2.6
SS8:	JNB P0.7,SS
	SETB P2.7
	RET